

Model : SQC460 (S)

Standby Power (50Hz)	460KVA/368KW
Prime Power(50Hz)	450KVA/360KW

Standard Features

- Engine: Cummins 6ZTAA13-G4
- Charge Alternator: 24V
- Governer: Electronic
- Generator: Stamford HCI544C
- Single Bearing Alternator IP23
- Insulation Class H/H
- Genuine radiator with engine driven fan
- Skid and vibration isolators
- Dry type air filter
- Main line circuit breaker (Below 500KVA)
- 12V battery and cable
- User's manual



Weight And Dimensions

Genset	Dimensions(LxWxH)	Weight (KG)
Open type	3250mmx1360mmx2100mm	3700
Silent type	5000mmx1983mmx2371mm	6450

Generator Ratings

Voltage	Hz	Phase	Power Factor	Standby (KVA/KW)	Prime (KVA/KW)
400/230	50	3	0.8	460/368	450/360

Criterion

- Generator sets: GB/T2820-1997, ISO9001: 2008
- Alternator: BS5000, VDE0530, NEMA MG1-32, IEC34, CSAC22.2-100, AS1359
- Diesel Engine: ISO3046, DIN6271



Engine Data

• Manufacturer/Model	DCEC Cummins 6ZTAA13-G4
• No.of Cylinders	6
• Displacement	13L
• Bore and Stroke	130*163(mm)
• Compression ratio	17:1
• Rated RPM	1500rpm
• Max.standby power at rated 1500RPM	415KW
• Aspiration	Turbocharged and Charge Air Cooled □
• Governor Type	Electronic
• Exhaust Gas Flow @Standby Rating	30.6kg/min
• Exhaust Temperature @Standby Rating	668°C
• Intake Air Flow@Standby Rating	29.2m ³ /min
• Fuel System	BYC PD/GAC
• 100%(Prime Power) Load	91.4Liter/H
• Lubrication System: Total system Capacity	45.42L
• Total Coolant Capacity	23.1L

Alternator Data

• Manufacture/Type	Stamford/HCI544C
• Number of phase power	3
• Factor	0.8
• Pole Number	4
• Bearing Number	1
• Exciter Type	Brushless, self-excited
• Insulation Class	H/H
• Protection	IP23

Control Panel



- Auto Module Control Panel, usually adopt control module of UK Deepsea DSE 6020 or Equal, is the configuration for nobody on duty generators control, This kind of panel adopts auto module control system, with large LCD display to show the menu.
- Features: receive remote output signal from ATS and realize auto start and stop of generators.
- Auto Mains Failure controller, can realize further more can detect ATS and control directly.





- Automatic Parallel Control Panel usually adopting intelligent control module of UK Deepsea DSE8610 or equal, this new automatic parallel system is inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for single genset working or Gensets Parallel working. This kind of panel also can be used to parallel generator when the capability of the power plant needs to be enlarged in the future.

Optional

Engine	Alternator	Fuel System	Control System
<ul style="list-style-type: none"> • Pre-heater 	<ul style="list-style-type: none"> • Anti Condensation Heater • Drop CT (For Paralleling) 	<ul style="list-style-type: none"> • Daily Fuel Tank • Water Separator 	<ul style="list-style-type: none"> • Remote Control Panel • Auto Transfer Switch (ATS) • Paralleling System • Electricity Output Cabinet

Others

- Rainproof Type
- Soundproof Type
- Trailer Type
- Container Type
- Spare Parts



Warranty

- Warranty is according to our standard conditions: 12 months or 1,200 running hours, subject to the earlier one. And what's more, Cummins gensets enjoy world-wide united Warranty from Cummins engine agency or service centre at the client's local side.
- Service and parts are available from Guangzhou Sanq Power Equipment Co.,Ltd or our distributors in your location.

