

Model : SQC825 (S)

Standby Power (50Hz)	825KVA/660KW
Prime Power(50Hz)	750KVA/600KW

Standard Features

- Engine: Cummins KTA38-G2
- Charge Alternator: 24V
- Governor: Electronic
- Generator: Stamford LVI634B
- Single Bearing Alternator IP23
- Insulation Class H/H
- Genuine radiator with engine driven fan
- Skid and vibration isolators
- Dry type air filter
- Main line circuit breaker (Below 500KVA)
- 12V battery and cable
- User's manual



Weight And Dimensions

Genset	Dimensions(LxWxH)	Weight (KG)
Open type	4200mmx1805mmx2383mm	7000
Silent type	6058mmx2438mmx2896mm	12200

Generator Ratings

Voltage	Hz	Phase	Power Factor	Standby (KVA/KW)	Prime (KVA/KW)
400/230	50	3	0.8	825/660	750/600

Criterion

- Generator sets: GB/T2820-1997, ISO9001: 2008
- Alternator: BS5000, VDE0530, NEMA MG1-32, IEC34, CSAC22.2-100, AS1359
- Diesel Engine: ISO3046, DIN6271



Engine Data

• Manufacturer/Model	CCEC Cummins KTA38-G2
• No.of Cylinders	12
• Displacement	37.8L
• Bore and Stroke	159*159(mm)
• Compression ratio	14.5:1
• Rated RPM	1500rpm
• Max.standby power at rated 1500RPM	731KW
• Aspiration	Turbocharged and aftercooled
• Governor Type	Electronic
• Exhaust Gas Flow @Standby Rating	2634L/S
• Exhaust Temperature @Standby Rating	552℃
• Intake Air Flow@Standby Rating	920liter/s
• Fuel System	Direct Injection Cummins PT
• 100%(Prime Power) Load	167Liter/H
• Lubrication System Min. capacity	87L
• Total Coolant Capacity	118L

Alternator Data

• Manufacture/Type	Stamford/LVI634B
• Number of phase power	3
• Factor	0.8
• Pole Number	4
• Bearing Number	1
• Exciter Type	Brushless, self-excited
• Insulation Class	H/H
• Protection	IP23

Control Panel



- Auto Module Control Panel, usually adopt control module of UK Deepsea DSE 7320 or Equal, is the configuration for nobody on duty generators control, This kind of panel adopts auto module control system, with large LCD display to show the menu.
- Features: receive remote output signal from ATS and realize auto start and stop of generators.
- Auto Mains Failure controller, can realize further more can detect ATS and control directly.
- RS232 or 485 interface which can communicate with PC to realize remote operation.





- Automatic Parallel Control Panel usually adopting intelligent control module of UK Deepsea DSE8610 or equal, this new automatic parallel system is inserted and folded installed, no need the peripheral relay and logic circuit. The main switch adopts electronic breaker or frame breaker, combined together with the generator, which is very reliable. One generator, one panel. The panel can be used both for single genset working or Gensets Parallel working. This kind of panel also can be used to parallel generator when the capability of the power plant needs to be enlarged in the future.

Optional

Engine	Alternator	Fuel System	Control System
<ul style="list-style-type: none"> • Pre-heater 	<ul style="list-style-type: none"> • Anti Condensation Heater • Drop CT (For Paralleling) 	<ul style="list-style-type: none"> • Daily Fuel Tank • Water Separator 	<ul style="list-style-type: none"> • Remote Control Panel • Auto Transfer Switch (ATS) • Paralleling System • Electricity Output Cabinet

Others

- Rainproof Type
- Soundproof Type
- Trailer Type
- Container Type
- Spare Parts



Warranty



- Warranty is according to our standard conditions: 12 months or 1,200 running hours, subject to the earlier one. And what's more, Cummins gensets enjoy world-wide united Warranty from Cummins engine agency or service centre at the client's local side.
- Service and parts are available from Guangzhou Sanq Power Equipment Co.,Ltd or our distributors in your location.

